


**PB-3**

**PB-3R**

**PB-7**

Designed for use on relay contacts, this pocket burnisher is the perfect tool for removing the oxide layer from the precious metals of relay contacts. These burnishers feature the following:

- Blade length and rigidity is adjustable by varying the depth of the blade in the chuck
- Plastic housing allows it to be used on live contacts without any shocks or shorts
- Removes the oxide layer or corrosion off contacts without leaving filings or debris

**PB-3** Includes (6) Flat 0.0035" Blades, stored in the opposite end of the pen

**PB-3R** Includes (6) Flat 0.0035" Blades and (6) 0.020" diameter Rods, stored in the opposite end of the pen

**PB-7** Includes (6) Flat 0.007" Blades, stored in the opposite end of the pen

SPECIFICATIONS	PB-3	PB-3R	PB-7
<b>BLADE TYPE</b>	Flat	Flat & Round	Flat
<b>BLADE THICKNESS</b>	0.0035" (0.089mm)	0.0035" (0.089 mm)	0.007" (0.018 mm)
<b>BLADE WIDTH</b>	3/16" (4.76 mm)	3/16" (4.76 mm)	3/16" (4.76 mm)
<b>BLADE LENGTH</b>	1 1/2" (38.10 mm)	1 1/2" (38.10 mm)	1 1/2" (38.10 mm)
<b>PEN LENGTH</b>	4 1/2" (114.3 mm)	4 1/2" (114.3 mm)	4 1/2" (114.3 mm)
<b>PEN DIAMETER</b>	3/8" (9.53 mm)	3/8" (9.525 mm)	3/8" (9.53 mm)
<b>WEIGHT</b>	0.068 lb (30.85 g)	0.069 lb (31.30 g)	0.069 lb (31.30 g)
<b>UPC #</b>	811490014398	811490014404	811490014411

